


Product datasheet

Specifications



EasyPact TVS coil 220 VAC 50 Hz spare part for LC1E300

LAEX7M5

Main

Range	Easy TeSys
Range of product	Easy TeSys Control
Product or component type	Contacteur coil
Device short name	LAEX
Product compatibility	LC1E300
Control circuit type	AC at 50 Hz standard
[Uc] control circuit voltage	220 V AC 50 Hz
Average resistance	1578 Ohm at 20 °C
Operating time	40...65 ms closing 100...170 ms opening
Maximum operating rate	2400 cyc/h 55 °C

Complementary

Inrush power in VA	650 VA 50 Hz cos phi 0.9 (at 20 °C)
Hold-in power consumption in VA	10 VA 50 Hz cos phi 0.3 (at 20 °C)
Heat dissipation	8 W

Environment

Ambient air temperature for operation	-5...55 °C
Net weight	0.77 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	9.0 cm
Package 1 Width	10.0 cm
Package 1 Length	18.5 cm
Package 1 Weight	874.0 g
Unit Type of Package 2	S02
Number of Units in Package 2	4
Package 2 Height	15.0 cm
Package 2 Width	30.0 cm

Package 2 Length	40.0 cm
Package 2 Weight	3.875 kg
Unit Type of Package 3	PAL
Number of Units in Package 3	64
Package 3 Height	70.0 cm
Package 3 Width	60.0 cm
Package 3 Length	80.0 cm
Package 3 Weight	66.48 kg

Contractual warranty

Warranty	18 months
-----------------	-----------

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[How this information helps you >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **Yes**

EU RoHS Directive **Pro-active compliance (Product out of EU RoHS legal scope)**

REACH Regulation [REACH Declaration](#)

China RoHS Regulation [China RoHS declaration](#)

Use Again

Repack and remanufacture

Circularity Profile [End of Life Information](#)

Take-back **No**